

1000kVA (800kW) Container Generator



Technical information:

Power	1000kVA (800kW) 400V / 50Hz
Motor control	electronic
Voltage regulation	automatic voltage regulator (AVR)
Environmental	liquid leakage monitoring (Bund Switch)
Sound pressure level to 7 meters	72 db(A)
Fuel tank	approx. 1300 liters (double wall for any sillage or leak)
Fuel consumption	approx. 200 liters/hour at maximum power
Weight approx.	16,800kg
Dimensions (L x W x H)	6,060mm x 2,440mm x 2,600mm
Extras	lockable, jacket water heater, battery charger
Connection	rail (bus bar) M12 via lug
Features:	robustly built
Runs on	heating oil, diesel or GTL
Switchable to	320V-460V at 50Hz / 320V-480V at 60Hz

Hint:

The data corresponds to the unit shown. Supplied units may have different data.